

Subtract Ino

Performs a subtraction between two images.
Images will become darker using subtraction.
Formula = Back - Fore

--- Inputs ---

When both input ports are connected, they will be combined in the process.
When the node Visibility switch is OFF it will display the Back port content.
If there is only one port connected, it will display its content.

Fore

Connect the image that will be overlaid on top.

Back

Connect the base image.

--- Settings ---

Opacity

Specifies the opacity of the image overlaid on top.
When 0 the Fore image will be transparent.
With the default value "1.0" , the Fore image will be composed as opaque.
Specify a value from 0 to 1.0.

Clipping Mask

When ON, it will take the Back port alpha information to define the alpha of the resulting image, leaving areas where the Alpha value is zero as transparent.
The default value is ON.

Alpha Rendering

This option is valid only when there is an Alpha channel.
When inactive, it masks the changes in the RGB values using the original Alpha of the image.
When active, the effect will be able to modify the Alpha channel, extending it as necessary to reproduce the full span of the effect.
The default setting is ON.